

GHL Logo Status Display

Some GHL devices have an illuminated logo which displays system information using a RGB-LED.



Up to 2 information can be displayed simultaneously according to the following rules:

- the information to be displayed are selected according to their priority
- if 2 information should be displayed, these appear alternately

Displayed information

	Information	Combinable with other information	Blinking can be switched off
Violet blinking	Device booting	No	No
Red/Yellow blinking	Error: Problem with serial number or security key	No	No
Red constant	Error: Memory defective	No	---
Yellow constant	Memory has been reset – please reactivate control by confirming on the device	No	---
Red blinking	Alarm	Yes	Yes
Yellow blinking	Warning	Yes	Yes
Green blinking	Activity, e.g. dosing or water change	Yes	Yes
White constant	Configuration LAN/Wi-Fi	No	---
White blinking	Connecting with myGHL	Yes	Yes
Blue blinking	Connected with myGHL	Yes	Yes
Blue constant	No information to display	---	---

(the order is according to the priority)

The user has some options to customize the display according to his wishes, he can choose among these modes:

- Standard – up to 2 information are shown, the logo might blink for displaying a certain information.
- Standard w/o Blinking – only one information can be displayed, the logo shows one color permanently.
- Off – no information is displayed, the logo is not illuminated.
- Constant Red, Green or Blue – no information is displayed, the logo is permanently illuminated with the selected color.

In addition, the brightness of the logo illumination can be set in the range of 20% to 100% (in the "off" mode, the brightness is independent of this always 0%).

System requirements

The functionality described here requires the following minimum software and firmware versions:

	Version
ProfiLux 3 N/T (eX)	6.26
GHL Doser 2 Standalone	1.19
GHL Doser 2 Slave	1.19
Expansion Box 2	2.02
GHL Control Center	1.0.8.3